## CONTROL4<sup>®</sup> ESSENTIAL CONTEMPORARY AUXILIARY KEYPAD



## CONTROL4® ESSENTIAL CONTEMPORARY AUXILIARY KEYPAD C4-V-AUX-C-WH

Control4's Contemporary Lighting is designed to elevate lighting control and aesthetics. With a beautiful design that suits the smart home of today, Contemporary Lighting gives you a new industrial design that customers will love.

Intelligent lighting is an essential part of every smart home and provides added convenience and peace of mind. Control4 Essential Wireless Lighting products are an addition to the Control4 Wireless Lighting product line and are designed with the essential features enabling them to be included with every Control4 system. The Control4<sup>®</sup> Essential Auxiliary Keypad provides a seamless solution for three-way control of an Essential switch or dimmer by wiring to the switch or dimmer using the existing wiring in the wall.

- Never come home to a dark house again
- Your home looks lived in when you are away
- Turn off *all* the lights as you run out the door
- Set the perfect lighting-level for everything-romantic dinners, parties, relaxing, cleaning
- Elegant, sophisticated design makes a beautiful addition to any home or business
- Color kits available in Black, Light Almond, and Snow White
- Control4<sup>®</sup> screw-less faceplates are sold separately, providing a sleek profile (see "Available accessories")



## **CONTROL4®** ESSENTIAL CONTEMPORARY AUXILIARY KEYPAD

| Model number                            | C4-V-AUX-C-WH  |
|---|--|
| Power requirements                      | 120-277V AC +/- 10% 60 Hz                                  |
| Installation features                   | Easy installation using convenient screw terminals         |
|   | Compatible with Essential Switches and Dimmers             |
|   | Each dimmer or switch supports up to 5 Auxiliary Keypads   |
| Environmental                           |  |
| Operational temperature                 | 0° C to 40° C (32° F to 104° F)                            |
| Humidity                                | 5% to 95% non-condensing                                   |
| Storage                                 | -20° C to 60° C (-4° F to 140° F)                          |
| Miscellaneous                           |  |
| Wallbox volume                          | 77.8 cubic centimeters (4.75 cubic inches)                 |
| Weight                                  | 0.10 kg (0.23 lb)  |
| Shipping weight                         | 0.11 kg (0.25 lb)  |
| Compatible devices                      |  |
| In-Wall Dimmer                          | C4-V-FPD120-WH , C4-V-FPD120-C-WH                          |
| In-Wall Switch                          | C4-V-SW120277-WH, C4-V-SW120277-C-WH                       |
| Available colors                        |  |
| Essential Auxiliary Keypad (C4-V-AUX-C) | Shipped in White (WH). Color-change kits avaiable.         |
| Color kit (C4-V-CKAUX-C-xx)             | White (WH), Light Almond (LA), Black (BL), Snow White (SW) |
| Available accessories                   |  |
|   |  |
| Faceplate, 1 gang (C4-V-FP1-C-xx)       | WH, LA, IV, BR, BL, GR, SW, MB, BI, SN, MS, VB             |

Faceplate, 2 gang (C4-V-FP2-C-xx) WH, LA, IV, BR, BL, GR, SW, MB, BI, SN, MS, VB

Gloss colors: WH=White, LA=Light Almond, IV=Ivory, BR=Brown, BL=Black, GR=Gray Satin colors: SW=Snow White, MB=Midnight Black, BI=Biscuit Metal finishes: SN=Satin Nickel, MS=Matte Stainless, VB=Venetian Bronze





Copyright ©2022, Snap One, LLC. All rights reserved. Snap One and its respective logos are registered trademarks or trademarks of Snap One, LLC (formerly known as Wirepath Home Systems, LLC), in the United States and/or other countries. Control4, SnapAV, Wirepath, and Wirepath ONE are also registered trademarks or trademarks of Snap One, LLC. Other names and brands may be claimed as the property of their respective owners. Snap One makes no claim that the information contained herein covers all installation scenarios and contingencies, or product use risks. Information within this specification subject to change without notice.

