

CONTROL4® OUTDOOR PLUG-IN OUTLET SWITCH



CONTROL4® OUTDOOR PLUG-IN OUTLET SWITCH

C4-V-OOSW120-BL

Intelligent lighting is an essential part of every smart home and provides added convenience and peace of mind. The Control4 Outdoor Plug-In Outlet Switch is a weatherproof plug-in switch that provides on/off control of 120V loads such as fountains, pumps, and outdoor lighting. Because it plugs into a standard 120V outlet, it can be easily installed without an electrician. Built-in Zigbee allows control through Control4 interfaces, lighting scenes, and programming. It also functions as a repeater, extending the range of the Zigbee network. A button on the front of the outlet allows it to be controlled locally.



CONTROL4® OUTDOOR PLUG-IN OUTLET SWITCH

Model | Control4 Outdoor Plug-In Outlet Switch
Model number | C4-V-OOSW120-BL

Power
Power requirements | 120V AC, 60 Hz


Load
Outlets | One controlled outlet
Maximum load | 600W incandescent, 1/2 HP motor, or 1800W resistive (15A)

Control
Control communications | 2.4 GHz (Zigbee IEEE 802.15.4) mesh networking
Range | Up to 45.7 m (150 feet) line of sight between the switch and the closest receiver module. For indoor use, place devices within 4.5 - 9 m (15 - 30 feet) of each other.

Environmental
Operating temperature | -10 °C to 40 °C (14 °F to 104 °F)
Storage temperature | -20 °C to 60 °C (-4 °F to 140 °F)
Weather resistance | Rainproof, meets NEMA Type 3R-Rainproof, UL 60730-1, CAN/CSA E60730-1 standards
Pollution degree | Degree 2. Normal, non-conductive, possibility of temporary conductivity due to condensation.

Mechanical
Dimensions (H × W × D) | 76 × 66 × 457 mm (3.0 × 2.6 × 18 in.)
Weight | 227 g (0.5 lb)
Available color | Black

MOST RECENT VERSION OF THIS DOCUMENT



ctrl4.co/oosw-ds

INSTALLATION GUIDE



ctrl4.co/oosw-ig