## CONTROL4® RECEPTACLE OUTLET SWITCH



## **CONTROL4® RECEPTACLE OUTLET SWITCH**

C4-V-ROSW120-xx

Intelligent lighting is an essential part of every smart home and provides added convenience and peace of mind. The Control4 Receptacle Outlet Switch provides an elegant way to invisibly control lamps and other plug-in devices in your Control4 system. It includes one always-on outlet, and one switched outlet for on/off control of virtually every 120V lighting load type, including LED lights, incandescent, halogens, compact fluorescents, and other plug-in devices. Built-in Zigbee allows control through Control4 interfaces, lighting scenes, and programming. It also functions as a repeater, extending the range of the Zigbee network. A button on the front of the outlet allows it to be controlled locally. Available in 8 stylish colors and finishes.



## **CONTROL4® RECEPTACLE OUTLET SWITCH**

Model Control4 Receptacle Outlet Switch

C4-V-ROSW120 Model number

Power

125V AC, 60 Hz Power requirements

Load

Outlets One pass through (top), one controlled (bottom)

1000W incandescent; 450W LED/CFL; 1800W (15A) resistive, 1/2 HP motor Supported load types

Total maximum load for both outlets: 1800W (15A) resistive Maximum load

Control

Control communications 2.4 GHz (Zigbee IEEE 802.15.4) mesh networking

> Up to  $45 \,\mathrm{m}$  (150 feet) line of sight between the switch and the closest receiver module. For normal use, place devices within  $4.5 - 9 \,\mathrm{m}$  (15 - 30 feet) of each other. Range

Environmental

Operational temperature 0 °C to 40 °C (32 °F to 104 °F)

> 5% to 95% non-condensing RH Humidity

Storage -20 °C to 60 °C (-4 °F to 140 °F)

Mechanical

Dimensions ( $H \times W \times D$ )  $29 \times 44 \times 105 \text{ mm} (1.13 \times 1.75 \times 4.13 \text{ in.})$ 

> Weight 173 g (0.38 lb)

Available colors\* BI, BL, BR, IV, LA, MB, SW, WH

> \*Gloss colors: WH=White, LA=Light Almond, IV=Ivory, BL=Black, BR=Brown Satin colors: BI=Biscuit, MB=Midnight Black, SW=Snow White



















ctrl4.co/rosw-ds





ctrl4.co/rosw-ig

